



8 x 8 Component, Composite, Analog Audio Matrix, Volume and Tone Controls, with Cat5 outputs

The Concord+ is an 8 input, 8 output matrix switch for HD Component video, composite or digital audio, and analog audio with volume, bass, and treble controls for each output. All inputs are RCA connector, and all outputs are RJ45 connectors. The Concord+ can transmit audio and video up to 1000 feet on Cat5e cables with outstanding video performance.

The receiver unit features a decora style insert with all six RCA connectors, and is powered completely from the Concord+ main unit.

Features

- * HD component video (YPbPr) up to 1000'
- * Composite or SPDIF switching
- * Analog stereo switching with Volume, Bass and Treble controls for each output.
- * Full non-blocking matrix - no routing limits
- * Decora style receiver
- * NeoTouch™ front panel - no moving parts to jam.
- * Multiple control inputs - RS-232, USB, IR detector (front) and wired IR (rear)
- * Highly visible Vacuum Fluorescent Display (VFD)
- * Separate front panel indicators for IR and RS232 activity
- * Front panel lockout, Front panel blackout

Designed and Manufactured in the USA by:

NeoPro
1594 Fayette St.
El Cajon, CA 92020
619-258-2000 sales & support
619-258-2135 fax
www.neoprointegrator.com



Specifications

Power Inlet:	IEC 320-C14
Input Voltage:	90-240VAC 50-60Hz, 25W typical
Dimensions:	Width: 17" Height: 3.45" Depth 10.5"
Weight:	12 lbs
Video Bandwidth:	140MHz+ (up to 1080p)
RS-232:	115.2K baud, full two way protocol
USB:	Slave device, Windows driver included, Installs as virtual COM port at 115.2K baud
Rear IR:	3.5mm mono jack for 5V or 12V blaster input, polarity insensitive

